

2094-AC32-M05

Allen Bradley Drives - Kinetix 6000

| Technical Specifications: | |
|---------------------------------|---------------------|
| Manufacturer | Rockwell Automation |
| Brand | Allen-Bradley |
| Part Number/Catalog No. | 2094-AC32-M05 |
| Module Type | Axis Module |
| Series | Kinetix 6000 |
| Efficiency | 0.95 |
| Continuous Current (RMS) | 34.6 Amps |
| Continuous Current (0 to peak) | 48.9 Amps |
| Line Loss Ride Through | 20 milliseconds |
| AC input voltage | 195 to 264 Volts AC |
| Internal Shunt Continuous Power | 200 Watts |
| Internal Shunt Peak Power | 5600 Watts |
| Bus Overvoltage | 425 Volts DC |
| Shunt On | 405 Volts DC |